4. Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN;**	**DVD-V540 Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc.No	Part No	Description ; Specification	Remark
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	

Loc.No	Part No	Description ; Specification	Remark
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	

Loc.No	Part No	Description ; Specification	Remark
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,-,-,-,-,-,-,-,-,-,	
SW602	AC34-00006A	SWITCH-REC;-,-,-,-,-,-,-,-,-,-,-,-,-	
W668	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	
XT602	2801-001381	CRYSTAL-UNIT;12MHz,30ppm,28-AAA,30pF,50o	
AUDIO/VIDEO PARTS			
C301F	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C315	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C317	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C318	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C319	2203-000843	C-CER,CHIP;39nF,10%,25V,X7R,TP,1608,-	
C320	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C321	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C322	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C325	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C326	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C327	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C328	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C329	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C330	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C331	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C332	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C333	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C334	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C334A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C335	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C336	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C337	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C338	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C344	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C345	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C348	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C349	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C350	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C353	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C354	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C355	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C355A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C393	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C395	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A01	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A09	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
C3A10	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C3A11	2301-000174	C-FILM,LEAD-PEF;15nF,5%,100V,TP,7.2x4.0x	Australia Only
	2301-001680	C-FILM,PEF;15nF,5%,50V,TP,6.	Other Only
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C3A15	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A16	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A21A	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,1608	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A29	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A30	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C3A70	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A71	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
C3Q1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3Q2	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C3Q3	2203-001086	C-CER,CHIP;0.005nF,0.25pF,50V,NP0,TP,160	
C3Q4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P1.25MM,STRAIGH	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002141	IC-VIDEO PROCESS;LA71730EM-MP	NT4.43 Only
	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	Other Only
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2434	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2534	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3Q1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q4	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q5	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q3Q6	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q3Q7	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A28	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R3Q1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3Q3	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q4	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3Q5	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q6	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3Q7	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q8	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q9	2001-000958	R-CARBON;750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W311	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15pp	Not used NT4.43
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	
HI-FI PARTS			
C501	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C502	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C503	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C504	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C505	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C506	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C507	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C508	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C510	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C517	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C518	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C519	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C520	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C521	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C522	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C523	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C524	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C525	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C535	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C536	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-002569	C-AL;2.2uF,20%,50V,GP,TP,4x5,2.5	
C541	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
D501	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R501	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R503	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R505	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R506	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R507	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R509	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R510	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R511	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R512	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R518	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R519	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R520	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R522	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R533	2007-000003	R-CHIP;43Kohm,5%,1/8W,TP,2012	
R540	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2007-000512	R-CHIP;2.4Kohm,5%,1/10W,TP,1608	
R546	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R547	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R552	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R553	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R570	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R571	2007-000098	R-CHIP;56Kohm,5%,1/10W,TP,1608	
A2/NICAM PARTS			
C4N01	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N02	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N03	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N06	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N07	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C4N08	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N09	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N10	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N11	2401-002186	C-AL;3.3UF,20%,50V,GP,BK,4X5,2.5	
C4N12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N14	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N16	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C4N17	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N18	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N19	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
C4N21	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N22	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N23	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N24	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N25	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC4N01	1204-001766	IC-AUDIO PROCESSOR;MSP3407D(PQFP),PQFP,4	Australia Only
	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(	Other Only
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N04	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
R4N01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R4N02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N04	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N05	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R4N06	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
J880	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J905	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J913	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001577	JACK-PIN;6P,3.5mm,NI,BLK,-	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q891A	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q891B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R891A	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R891B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R892A	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R892B	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R893A	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R893B	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
DISPLAY/FUNCTION MATRIX PARTS			
BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD702	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C712	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
CN701	3710-001918	CONNECTOR-SOCKET;6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
JK701	3722-001943	JACK-PIN;3P,8.3PI,NI,BLK,-	
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW708	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW709	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW710	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW713	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW714	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW715	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW716	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
W735	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
W737	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN;**	**DVD-V440 Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,

Loc.No	Part No	Description ; Specification	Remark
C326	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C327	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C328	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C329	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C330	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C331	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C332	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C333	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C334	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C334A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C335	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C336	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C337	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C338	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C344	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C345	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C348	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C349	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C350	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C353	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C354	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C355	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C355A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C393	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C395	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A01	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A09	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
C3A10	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C3A11	2301-000174	C-FILM,LEAD-PEF;15nF,5%,100V,TP,7.2x4.0x	Australia Only
C3A11	2301-001680	C-FILM,PEF;15nF,5%,50V,TP,6.	Other Only
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C3A15	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A16	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A21A	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,1608	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A29	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A30	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C3A70	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A71	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
C3Q1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3Q2	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C3Q3	2203-001086	C-CER,CHIP;0.005nF,0.25pF,50V,NP0,TP,160	
C3Q4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P,1.25MM,STRAIGH	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	

Loc.No	Part No	Description ; Specification	Remark
IC301	1204-002141	IC-VIDEO PROCESS;LA71730EM-MP	NT4.43 Only
IC301	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	Other Only
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2434	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2534	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3Q1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q4	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q5	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q3Q6	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q3Q7	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A28	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R3Q1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3Q3	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q4	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3Q5	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q6	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3Q7	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q8	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q9	2001-000958	R-CARBON;750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W311	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15pp	Not used NT4.43
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	
HI-FI PARTS			
C501	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C502	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C503	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C504	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C505	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C506	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C507	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C508	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C510	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C517	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C518	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C519	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C520	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C521	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C522	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C523	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C524	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C525	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C535	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C536	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-002569	C-AL;2.2uF,20%,50V,GP,TP,4x5,2.5	
C541	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
D501	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
R501	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R503	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R505	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R506	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R507	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R509	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R510	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R511	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R512	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R518	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R519	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R520	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R522	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R533	2007-000003	R-CHIP;43Kohm,5%,1/8W,TP,2012	
R540	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2007-000512	R-CHIP;2.4Kohm,5%,1/10W,TP,1608	
R546	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R547	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R552	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R553	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R570	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R571	2007-000098	R-CHIP;56Kohm,5%,1/10W,TP,1608	
A2/NICAM PARTS			
C4N01	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N02	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N03	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N06	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N07	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N08	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N09	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N10	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N11	2401-002186	C-AL;3.3UF,20%,50V,GP,BK,4X5,2.5	
C4N12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N14	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N16	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C4N17	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C4N18	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N19	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
C4N21	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N22	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N23	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N24	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N25	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC4N01	1204-001766	IC-AUDIO PROCESSOR;MSP3407D(PQFP),PQFP,4	Australia Only
IC4N01	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(	Other Only
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N04	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
R4N01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R4N02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N04	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N05	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R4N06	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
J880	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J905	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J913	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001577	JACK-PIN;6P,3.5mm,NI,BLK,-	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q891A	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q891B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R891A	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R891B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R892A	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R892B	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R893A	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R893B	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
DISPLAY/FUNCTION MATRIX PARTS			
BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD702	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C712	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
CN701	3710-001918	CONNECTOR-SOCKET,6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
JK701	3722-001943	JACK-PIN;3P,8.3PI,NI,BLK,-	
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW708A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW709A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW710A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW711A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW712A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW714A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW715A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
W735	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
W737	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN;**	**DVD-V340 Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P1A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P1B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R1P2A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P2B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	

Loc.No	Part No	Description ; Specification	Remark
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,	
SW602	AC34-00006A	SWITCH-REC;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-	
W668	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	
XT602	2801-001381	CRYSTAL-UNIT;12MHz,30ppm,28-AAA,30pF,50o	
AUDIO/VIDEO PARTS			
C301F	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C315	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C317	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C318	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C319	2203-000843	C-CER,CHIP;39nF,10%,25V,X7R,TP,1608,-	
C320	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	

Loc.No	Part No	Description ; Specification	Remark
C321	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C322	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C325	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C326	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C327	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C328	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C329	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C330	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C331	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C332	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C333	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C334	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C334A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C335	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C336	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C337	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C338	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C344	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C345	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C348	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C349	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C350	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C353	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C354	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C355	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C355A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C393	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C395	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A01	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A09	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
C3A10	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C3A11	2301-001680	C-FILM,PEF;15nF,5%,50V,TP,6.3x3x7mm,-	
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C3A15	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A16	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A21A	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,1608	
C3A22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A29	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A30	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C3A51	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A52	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A53	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A54	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A70	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A71	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3Q1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3Q2	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C3Q3	2203-001086	C-CER,CHIP;0.005nF,0.25pF,50V,NP0,TP,160	
C3Q4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
CN301	3708-000394	CONNECTOR-FPC/FFC/PIC,6P,1.25MM,STRAIGHT	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC,6P,1.25MM,STRAIGHT	
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	NT4.43 Only
IC301	1204-002141	IC-VIDEO PROCESS;LA71730EM-MP	Other Only
IC302	1204-001748	IC-SELECTOR;MM1503XN,SOP,6P,63MIL,PLASTI	
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2434	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2534	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,TO-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,TO-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,TO-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3Q1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q4	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q5	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q3Q6	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q3Q7	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A27	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3A28	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3A29	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R3A31	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A32	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R3A33	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R3Q1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3Q3	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q4	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3Q5	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q6	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3Q7	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q8	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q9	2001-000958	R-CARBON;750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W311	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15pp	Not used NT4.43
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	

Loc.No	Part No	Description ; Specification	Remark
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C840	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,	Not used NT4.43
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C857	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,	Not used NT4.43
D805	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
J880	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001575	JACK-PIN;4P/6P,3.5mm,NI,BLK,-	
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	Not used NT4.43
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	Not used NT4.43
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q802	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,	Not used NT4.43
Q803	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,	Not used NT4.43
Q804	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,	Not used NT4.43
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q811	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN	Not used NT4.43
R801A	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,160	Not used NT4.43
R802	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,16	Not used NT4.43
R803	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,16	Not used NT4.43
R805	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,160	Not used NT4.43
R806	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,160	Not used NT4.43
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R843	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,160	Not used NT4.43
R844	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	Not used NT4.43
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD801	0403-000297	DIODE-ZENER;MTZ6.2B,5.96-6.27	Not used NT4.43
ZD805	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3	Not used NT4.43
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD811	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.0	Not used NT4.43
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD863	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23	Not used NT4.43
DISPLAY/FUNCTION MATRIX PARTS			
BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	

This Document can not be used without Samsung's authorization

Loc.No	Part No	Description ; Specification	Remark
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
CN701	3710-001918	CONNECTOR-SOCKET;6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
J01C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J02C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J10C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J701A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
JK701	3722-002170	JACK-PIN;2P,Ni,WHT/YEL,ANGLE	
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW708	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW710	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW711	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW712	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW713	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW714	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW715	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN,**	**Iran Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc.No	Part No	Description ; Specification	Remark
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C698	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q603	0504-000126	TR-DIGITAL;KSR1101,NPN,200mW,4.7K/4.7K,S	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,

Loc.No	Part No	Description ; Specification	Remark
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
FL3D01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002141	IC-VIDEO PROCESS;LA71730EM-MPB-E,QFP,100	
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A50	2702-000119	INDUCTOR-RADIAL;150uH,5%,6.0x6.4mm	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2434	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2534	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q3D01	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3D02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3D07	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q3Q1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q4	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3Q5	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q3Q6	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q3Q7	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A28	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R3D01	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3D02	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R3D03	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3D04	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3Q1	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3Q3	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q4	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3Q5	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q6	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3Q7	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q8	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
R3Q9	2001-000958	R-CARBON;750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W311	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15ppm,28-AAA,S,	
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	

Loc.No	Part No	Description ; Specification	Remark
HI-FI PARTS			
C501	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C502	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C503	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C504	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C505	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C506	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C507	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C508	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C510	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C517	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C518	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C519	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C520	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C521	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C522	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C523	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C524	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C525	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C535	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C536	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-002569	C-AL;2.2uF,20%,50V,GP,TP,4x5,2.5	
C541	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
D501	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
R501	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R503	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R505	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R506	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R507	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R509	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R510	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R511	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R512	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R518	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R519	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R520	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R522	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R533	2007-000003	R-CHIP;43Kohm,5%,1/8W,TP,2012	
R540	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2007-000512	R-CHIP;2.4Kohm,5%,1/10W,TP,1608	
R546	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R547	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R552	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R553	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R570	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R571	2007-000098	R-CHIP;56Kohm,5%,1/10W,TP,1608	
A2/NICAM PARTS			
C4N01	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N02	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N03	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N06	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N07	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N08	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N09	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N10	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N11	2401-002186	C-AL;3.3UF,20%,50V,GP,BK,4X5,2.5	
C4N12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N14	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N16	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C4N17	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N18	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N19	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
C4N21	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N22	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N23	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N24	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N25	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC4N01	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(PQFP),PQFP,4	
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N04	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
R4N01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R4N02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N04	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N05	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R4N06	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
J880	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J905	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J913	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001577	JACK-PIN;6P,3.5mm,NI,BLK,-	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
LD01	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q891A	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q891B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R891A	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R891B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R892A	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R892B	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R893A	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R893B	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

DISPLAY/FUNCTION MATRIX PARTS

BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD702	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C712	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
CN701	3710-001918	CONNECTOR-SOCKET;6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
JK701	3722-001943	JACK-PIN;3P,8.3PI,NI,BLK,-	
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW707A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW708	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW708A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW709	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW709A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW710	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW710A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW711A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW712A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW713	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW714	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW714A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW715	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
SW715A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	DVD-V27000 Only
SW716	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	DVD-V28000 Only
W735	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
W737	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN**	**SV-DVD340 Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P1A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P1B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R1P2A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P2B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	

Loc.No	Part No	Description ; Specification	Remark
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,	
SW602	AC34-00006A	SWITCH-REC;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	
XT602	2801-001381	CRYSTAL-UNIT;12MHz,30ppm,28-AAA,30pF,50o	
AUDIO/VIDEO PARTS			
C301F	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C315	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C317	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C318	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C319	2203-000843	C-CER,CHIP;39nF,10%,25V,X7R,TP,1608,-	
C320	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C321	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C322	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C325	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C326	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C327	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C328	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C329	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C330	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C331	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C332	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C333	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C334	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C334A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C335	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C336	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C337	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C338	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C344	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C345	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C348	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C349	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C350	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C353	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C354	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C355	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C355A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C392	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A01	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A09	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
C3A10	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C3A11	2301-001680	C-FILM,PEF;15nF,5%,50V,TP,6.3x3x7mm,-	
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C3A15	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A16	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A21A	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,1608	
C3A22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A29	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A30	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C3A51	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A52	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A53	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A54	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A70	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A71	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CN301	3708-000394	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	
IC302	1204-001748	IC-SELECTOR;MM1503XN,SOP,6P,63MIL,PLASTI	
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q302	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R324	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R350	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A27	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R3A28	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R3A29	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R3A31	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A32	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R3A33	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
W311	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	
SECAM PARTS			
C3S01	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3S02	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S03	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3S04	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S05	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S06	2401-001324	C-AL;0.47UF,20%,50V,GP,BK,3X5,2.5	
C3S07	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
C3S08	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S09	2401-001324	C-AL;0.47UF,20%,50V,GP,BK,3X5,2.5	
C3S10	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3S11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S12B	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C3S14	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C3S14B	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C3S15	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
IC3S01	1204-001921	IC-CHROMA;LA70100M,SOP,30P,375MIL,PLASTI	
R3S01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R3S02	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C840	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C857	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
D805	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
J880	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J881A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J882A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J883A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001574	JACK-SCART;21P,-,SN,BLK,#20-28	
JC802	AC37-22002P	JACK-PIN;3.2mm,DPAM-9837,2P(1),MONO,SV-	
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q802	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q803	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q804	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q811	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
R801A	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
R802	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R803	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R805	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R806	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R843	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R844	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD801	0403-000297	DIODE-ZENER;MTZ6.2B,5.96-6.27V,500MW,DO-	
ZD805	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD811	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD863	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
DISPLAY/FUNCTION MATRIX PARTS			
BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	

This Document can not be used without Samsung's authorization

Loc.No	Part No	Description ; Specification	Remark
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
CN701	3710-001918	CONNECTOR-SOCKET;6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
J01C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J02C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J10C	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J701A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
JK701	3722-002170	JACK-PIN;2P,Ni,WHT/YEL,ANGLE	
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW708A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW709A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW710A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW711A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW712A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW714A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW715A	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN;**	**CIS Only**
S.M.P.S PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1S02	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SD12	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C1SD13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C1SD16	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C1SF02	2401-002608	C-AL;33uF,20%,35V,GP,TP,5x11,5	
C1SS01	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS02	2301-001157	C-FILM,LEAD-PEF;47nF,10%,275V,BK,17.5x12	⚠
C1SS03	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS05	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS06	2201-002044	C-CERAMIC,DISC;0.1NF,10%,400V,Y5P,TP,8.5	⚠
C1SS10	2401-003303	C-AL;82uF,20%,400V,GP,BK,22X30,10	
C1SS11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1SS12	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1SS15	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS16	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS21	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS22	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS26	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
C1SS27	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
CN01	3711-005565	CONNECTOR-HEADER;NOWALL,24P,1R,2mm,STRAI	
CN1SS1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SF01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1SF02	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS13	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS14	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,-,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1A,DO-204AC,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
FZ01	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
FZ02	3601-001240	FUSE-RADIAL LEAD;50V,1A,-,-,5.0x4.0x5.0m	
IC1S02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
IC1SS2	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	
L1SS02	AC29-00003A	FILTER LINE NOISE;-,20mH MIN,-,-,-	⚠
L1SS03	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00012J	TRANS SWITCHING;EER-3126,SLV-D950E,-,-,-	⚠
R1SD11	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD13	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SD14	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF05	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SF06	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SF07	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SQ11	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SR01	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR02	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SR03	2001-000548	R-CARBON;270KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS01	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS08	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc.No	Part No	Description ; Specification	Remark
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
ZD1SS1	0403-000713	DIODE-ZENER;MTZJ20B,18.63-17.7V,500MW,DO	
ZD1SS2	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500MW,DO	
POWER DRIVER PARTS			
C1P101	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-002026	C-AL;10UF,20%,35V,GP,TP,5X5,2.5	
C1P104	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C1P105	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P115	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C1P116	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P106	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D1P130	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P102	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q1P101	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P105	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P106	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P107	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
Q1P111	0501-000362	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1000MW,TO	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P122	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
R1P3A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP	Not used SV-DVD546/DVD645
R1P4A	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,4.94-5.2V,500MW,DO-	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C603	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C604	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C606	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
C606A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C607A	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	
C609	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C610	2401-003336	C-AL;4.7UF,20%,50V,GP,TP,5X5,2	
C611	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C612	2203-000726	C-CER,CHIP;3.9nF,10%,50V,X7R,TP,1608,-	
C613	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C614	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C615	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
C616	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C617	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C618A	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C619	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C619A	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C620	2401-001543	C-AL;47uF,20%,25V,GP,TP,6.3x5mm,2.5	
C621	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C621A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C623	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C624	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C625	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C626	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C627	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C628	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C628A	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C629	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608	
C630	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C633	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C637	2203-001662	C-CER,CHIP;5.6NF,10%,50V,X7R,TP,1608	
C645	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C659A	2203-001140	C-CER,CHIP;68nF,10%,16V,X7R,TP,1608	
C660	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C661	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C661A	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C662	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C663	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C664	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C691	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C695	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608	
C699A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C699B	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
CN604	AC37-00027A	CONNECTOR-HEADER;20045WS,X-11,T8.5,W17.4	
D603	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D604	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC601	AC09-00515A	IC MICOM;M3776AMFA-103GP,DVD-V540,100P,	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001150	IC-EEPROM;24C081,1Kx8,DIP,8P,9.2x6.4mm,2	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
J602	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L601	2701-000114	INDUCTOR-AXIAL;10UH,10%,2534	
L602	2701-000238	INDUCTOR-AXIAL;1.8UH,10%,2534	
L603	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
LD601	0601-001817	LED-IR;SIDE-VIEW,2.5mm,75mW,6V,940,TR	
PT601	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
PT602	0604-001275	PHOTO-INTERRUPTER;-,-,-,SNAP,TR	
Q601	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
R601	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
R602	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
R603	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R604	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R608	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R613	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R617	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R621A	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R630	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R631	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R632	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R633	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R634	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R635	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R636	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R640	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R641	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R643	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R657	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
R660	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R661	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R667	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R668	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R671	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R674	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R679	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R682	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R685	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R688	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R691	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R693	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R694	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R698	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
S602	0603-001134	PHOTO TR;-,30V,4V,50mA,75mW,TRAY	
SW601	AC34-00005A	SWITCH MODE;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-	
SW602	AC34-00006A	SWITCH-REC;-,-,-,-,-,-,-,-,-,-,-,-,-,-,-,-	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	
XT602	2801-001381	CRYSTAL-UNIT;12MHz,30ppm,28-AAA,30pF,50o	
AUDIO/VIDEO PARTS			
C301F	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C315	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C317	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C318	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C319	2203-000843	C-CER,CHIP;39nF,10%,25V,X7R,TP,1608,-	
C320	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C321	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C322	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C325	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C326	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	

Loc.No	Part No	Description ; Specification	Remark
C327	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C328	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C329	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C330	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C331	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C332	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C333	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C334	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C334A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C335	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C336	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C337	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
C338	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C344	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
C345	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C347	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C348	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C349	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
C350	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C353	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C354	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C355	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
C355A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C392	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A01	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A09	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
C3A10	2203-001211	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,1608	
C3A11	2301-001680	C-FILM,PEF;15nF,5%,50V,TP,6.3x3x7mm,-	
C3A12	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C3A14	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C3A15	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3A16	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A21A	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,1608	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A29	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3A30	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
C3A70	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
C3A71	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P,1.25MM,STRAIGH	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A02	AC37-00028A	CONNECTOR-SOCKET;-,X-11,T9.0,W8.5,PBT NT	
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	
J330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
L301	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L301A	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L302	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L303	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L304	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	

Loc.No	Part No	Description ; Specification	Remark
L370	2701-000113	INDUCTOR-AXIAL;100UH,5%,2534	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A03	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L3A70	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
Q301F	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
Q302	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R301F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R302F	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
R315	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R316	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R320	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R322	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
R323	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
R324	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R329	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
R330	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R331	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R350	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
R360	2007-001196	R-CHIP;820Kohm,5%,1/10W,TP,1608	
R372	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R373	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R380	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A01	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A04	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A05	2007-000616	R-CHIP;24Kohm,5%,1/10W,TP,1608	
R3A06	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
R3A07	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	
R3A08	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
R3A11	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R3A13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R3A14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A16	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A17	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A18	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
R3A24	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
R3A25	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A28	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
R3A50	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R3A60	2007-000704	R-CHIP;3.6Kohm,5%,1/10W,TP,1608	
R3A70	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
W177	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W178	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C401A	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C401B	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C402	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
C403	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C404	2401-001077	C-AL;330nF,20%,50V,GP,TP,4x7mm,5mm	
C405	2401-002438	C-AL;47uF,20%,50V,WT,TP,6.3x11,5	
C406	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D401	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L401	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
Q401	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2007-001010	R-CHIP;51Kohm,5%,1/10W,TP,1608	
R408	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R440	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R441	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
TM401	AC40-00029A	TM BLOCK;TCMK0601PD20A,PAL B/G + I + D/	
W404	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,31.4-34.6V,1000MW,DO-	
HI-FI PARTS			
C501	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C502	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C503	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C504	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C505	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C506	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C507	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C508	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C510	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C517	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C518	2401-000909	C-AL;22uF,20%,16V,GP,TP,5x5,2.5	
C519	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C520	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C521	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C522	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C523	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C524	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C525	2401-001249	C-AL;4.7uF,20%,35V,GP,TP,4x5,2.5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C535	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C536	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-002569	C-AL;2.2uF,20%,50V,GP,TP,4x5,2.5	
C541	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5	
D501	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
R501	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R503	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R505	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R506	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R507	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R509	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R510	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R511	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R512	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R518	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R519	2007-001056	R-CHIP;6.2Kohm,5%,1/10W,TP,1608	
R520	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
R522	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R533	2007-000003	R-CHIP;43Kohm,5%,1/8W,TP,2012	
R540	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2007-000512	R-CHIP;2.4Kohm,5%,1/10W,TP,1608	
R546	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R547	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R552	2007-000913	R-CHIP;43Kohm,5%,1/10W,TP,1608	
R553	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
R570	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R571	2007-000098	R-CHIP;56Kohm,5%,1/10W,TP,1608	
SECAM PARTS			
C3S01	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3S02	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S03	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C3S04	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S05	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S06	2401-001324	C-AL;0.47UF,20%,50V,GP,BK,3X5,2.5	
C3S07	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
C3S08	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S09	2401-001324	C-AL;0.47UF,20%,50V,GP,BK,3X5,2.5	
C3S10	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3S11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C3S12A	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,16	Not used SV-DVD546/DVD645
C3S12B	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C3S14	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C3S14A	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,16	Not used SV-DVD546/DVD645
C3S14B	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C3S15	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
IC3S01	1204-001921	IC-CHROMA;LA70100M,SOP,30P,375MIL,PLASTI	
R3S01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R3S02	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
A2/NICAM PARTS			
C4N01	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N02	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N03	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N06	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C4N07	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N08	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
C4N09	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N10	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N11	2401-002186	C-AL;3.3UF,20%,50V,GP,BK,4X5,2.5	
C4N12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N14	2401-000408	C-AL;10uF,20%,16V,GP,TP,3.5x5,2.5	
C4N15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N16	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C4N17	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N18	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
C4N19	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
C4N21	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N22	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N23	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N24	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N25	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C4N30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
IC4N01	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(PQFP),PQFP,4	
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N04	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
R4N01	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R4N02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N04	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N05	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
R4N06	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
INPUT-OUTPUT PARTS			
C818	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C819	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C820	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C821	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608	
C822A	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
C835	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
C840	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C853	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C854	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
C857	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
D805	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
J881A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J882A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J883A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J905	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J910	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J911	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J913	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
J914	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001574	JACK-SCART;21P,-,SN,BLK,#20-28	
JC802	AC37-22002N	JACK-PIN;3.2mm,DPAE-9836,3P(1),HI-FI,SV	
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q802	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q803	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,47K/47K,SOT	
Q804	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q806	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4.7K,S	
Q810	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q811	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
Q891A	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q891B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R801A	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
R802	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R803	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	
R805	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R806	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R807	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	
R813	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R814	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R815	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R816	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608	
R822B	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R842	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	
R843	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
R844	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
R851	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R852	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
R891A	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R891B	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R892A	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R892B	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
R893A	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R893B	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
R894A	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
R894B	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
ZD801	0403-000297	DIODE-ZENER;MTZ6.2B,5.96-6.27V,500MW,DO-	
ZD805	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO-	
ZD806	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD807	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD811	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD851	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD852	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD853	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD854	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	
ZD863	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
DISPLAY/FUNCTION MATRIX PARTS			
BD701	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used SV-DVD546/DVD645
BD702	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used SV-DVD546/DVD645
BD703	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used SV-DVD546/DVD645
C701	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C702	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C703	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
C706	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	Not used SV-DVD546/DVD645
C707	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C708A	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
C712	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	Not used SV-DVD546/DVD645
C714	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	Not used SV-DVD546/DVD645
CN701	3710-001918	CONNECTOR-SOCKET;6P,1R,2MM,ANGLE,SN	
CN701A	3711-005312	CONNECTOR-HEADER;3WALL,6P,1R,2MM,STRAIGH	
D701	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D702	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D703	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D704	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
D705	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	
DT701	AC07-00069A	LED DISPLAY;BCD-9027E,SV-DVD440,5-DIGIT,	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
JK701	3722-001943	JACK-PIN;3P,8.3PI,NI,BLK,-	Not used SV-DVD546/DVD645
L701	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
L702	2701-000002	INDUCTOR-AXIAL;100UH,10%,4298	
R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R703	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
R704	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	Not used SV-DVD546/DVD645
RM701	AC32-00006A	MODULE REMOCON;TSOP2238WE1,38KHZ,-,5.08m	
SW701	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW702	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW703	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW704	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW705	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW707	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW708	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW709	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW710	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW711	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	SV-DVD546/DVD645 Only
SW712	3404-001182	SWITCH-TACT;DC12V,50MA,100GF	SV-DVD546/DVD645 Only
SW713	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,	Not used SV-DVD546/DVD645
SW714	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW715	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
SW716	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,0	Not used SV-DVD546/DVD645
W735	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
W737	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
ZD701	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V	Not used SV-DVD546/DVD645

Loc.No	Part No	Description ; Specification	Remark
602		**ASSY PCB-DVD;**	
AC14	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
AC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC19	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC21	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
AC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC25	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
AC26	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
AC27	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AC5	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
AC9	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
ACC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
ACC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
AD1	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD2	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD40	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
AE10	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
AE11	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AE13	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AE14	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
AE3	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AE4	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
AE5	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AE8	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
AE9	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
AEE1	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AEE2	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AEE50	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AEE51	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
AIC2	1002-001294	IC-D/A CONVERTER;PCM1742KE,24BIT,TSSOP,1	
AIC4	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
AIC5	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
AL1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
AL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
AL3	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
AL4	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
AQ1	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ2	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ20	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ21	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ4	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ40	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ41	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ5	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ6	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AR1	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AR14	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
AR15	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR16	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR17	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR18	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR28	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
AR29	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR3	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AR30	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR31	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR32	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
AR35	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
AR40	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
AR41	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
AR42	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
AR43	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
AR46	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
AR47	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
AR48	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
AR49	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AR50	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
ARR1	2007-000939	R-CHIP;47Kohm,1%,1/10W,TP,1608	
ARR2	2007-000939	R-CHIP;47Kohm,1%,1/10W,TP,1608	
ARR3	2007-000939	R-CHIP;47Kohm,1%,1/10W,TP,1608	
ARR4	2007-000939	R-CHIP;47Kohm,1%,1/10W,TP,1608	
ARR40	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
ARR41	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
ARR5	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
ARR50	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ARR51	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ARR6	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AZ1	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
AZ2	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
AZ3	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
AZ4	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
BD01	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
BD02	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
C10	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
C7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
C9	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
CC1	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
CC10	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
CC12	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
CC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC17	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-	
CC2	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
CC20	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608	
CC21	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
CC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC23	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
CC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC25	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608	
CC26	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC27	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC28	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
CC3	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
CC30	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
CC31	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
CC32	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
CC33	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	
CC34	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CC35	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
CC36	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
CC37	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
CC4	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
CC5	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,TP,1608	
CC8	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
CCC01	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC02	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC03	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC04	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC05	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC06	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC07	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC08	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
CCC09	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC10	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
CCC13	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CCC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
CCC16	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC19	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC21	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CCC23	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
CJ300	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
CN41	3710-002050	CONNECTOR-SOCKET;12P,1R,2mm,STRAIGHT,SN,	
CN42	3710-002050	CONNECTOR-SOCKET;12P,1R,2mm,STRAIGHT,SN,	
CNL1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
CNL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
CVL0	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used CIS
CVL1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used CIS
CVL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	Not used CIS
DABD1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
DAC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X	Not used SV-DVD340/440/641/645
DAC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
DAE2	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	Not used SV-DVD340/440/641/645
DAL1	2703-000398	INDUCTOR-SMD;10uH,10%,3	Not used SV-DVD340/440/641/645
DAL3	2901-001273	FILTER-EMI SMD;50V,2A,-,220pF,3.2x1.6x0.	
DAR1	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
DAR2	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608	
DAR24	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DAR3	2007-000075	R-CHIP;220ohm,5%,1/10W,TP	Not used SV-DVD340/440/641/645
DAZ1	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
DAZ2	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
DCON1	3708-001266	CONNECTOR-FPC/FFC/PIC;11P,1MM,STRAIGHT,S	
DCON3	3708-001696	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S	
DIC2	1107-001369	IC-FLASH MEMORY;29LV800,1Mx8/512Kx16,TSO	
DIC3	1103-001204	IC-EEPROM;24C021,256x8,SOP,8P,5.13x3.95m	
DIC4	0801-002701	IC-CMOS LOGIC;74VHCT125A,BUFFER,TSSOP,14	
DIC5	1105-001513	IC-DRAM;IS42S16400A-7T,1Mx16Bitx4Bit,T	
DJP10	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DJP11	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DJP2	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
DOIC2	3707-001065	CONNECTOR-OPTICAL;PLUG,	Not used SV-DVD340/440/641/645
DY1	2801-004279	CRYSTAL-UNIT;27.00MHz,10ppm,28-AAA,20pF,	
ECC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
ECC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
FB2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
JACK1	3722-002059	JACK-PIN;6P(6P),-,RED/WHT/BLU/BLK/GRY,A	
	3722-002128	JACK-PIN;3P,SN/NI,RED/WHT/	CIS Only
JL1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
JL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
LDD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
LDD2	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
LDQ1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
LDQ2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
LDQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
LDR1	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
LDR2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
LDR3	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	
LDR4	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
LDR5	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
LDR6	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
LPC2	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
LPC3	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
LPC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
LPE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
LPE2	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
LPR1	2007-000312	R-CHIP;10ohm,5%,1/4W,TP,3216	
LPR2	2007-000965	R-CHIP;5.1Kohm,5%,1/10W,TP,1608	
LPR3	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
LPR4	2007-000312	R-CHIP;10ohm,5%,1/4W,TP,3216	

Loc.No	Part No	Description ; Specification	Remark
MC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
MCE1	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
MCE2	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
MCE3	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
MD1	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
MIC1	1003-001661	IC-MOTOR DRIVER;FAN8004,HQFP,48P,13.2x13	
MIC2	1201-001842	IC-OP AMP;TL3472CD,SO,TP,8P,-,DUAL,-,PAL	
MPE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
MR1	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR10	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR11	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR12	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
MR13	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
MR14	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
MR15	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR16	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
MR17	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR18	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
MR2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR25	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	
MR26	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR3	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	
MR4	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
MR5	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
MR6	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
MR7	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
MR8	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR9	2007-000127	R-CHIP;9.1Kohm,5%,1/10W,TP,1608	
MTR4	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MTR5	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MTR6	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
opr10	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	
OPR11	2007-000083	R-CHIP;3Kohm,5%,1/10W,TP,1608	
OPR13	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
PAC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PAE11	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PL2	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
PPBD1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
PPC1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PPC118	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PPC2	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PPC3	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PPC80	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PPC81	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PPC82	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
PPE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PPE110	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
PPE18	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
PPE2	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PPE25	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
PPE3	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PPE4	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
PPIC2	1203-003132	IC-POSI.ADJUST REG.;AMC1117,SOT-223,3P,6	
PPIC3	1203-003216	IC-POSI.FIXED REG.;G9133,TO-220F,4P,10.1	
PPIC5	1203-000293	IC-POSI.FIXED REG.;7808,TO-220,3P,-,PLAS	
PPL10	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
PPL12	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
PPL2	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
PPL80	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
PPR1	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
PPR2	2007-000343	R-CHIP;120ohm,1%,1/10W,TP,1608	
PPR3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
QLP1	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	

Loc.No	Part No	Description ; Specification	Remark
QLP2	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	
R10	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R13	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
R36	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R38	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R39	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R40	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R41	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R42	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
R46	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R47	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
R7	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R73	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R8	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
R9	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
RAR11	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC19	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
RC20	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC21	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC22	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
RC23	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC25	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
RC28	2203-001222	C-CER,CHIP;0.82NF,10%,50V,X7R,TP,1608	
RC29	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC31	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC32	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
RC33	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608	
RC34	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
RC35	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
RC36	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
RC37	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
RC6	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC7	2203-001634	C-CER,CHIP;33nF,10%,50V,X7R,TP,1608,1.6m	
RC8	2203-000405	C-CER,CHIP;0.18NF,5%,50V,C0G,TP,1608	
RC9	2203-000560	C-CER,CHIP;220nF,+80-20%,25V,Y5V,TP,1608	
RCL23	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,150mA,,,,	
RE10	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
RIC1	1204-002223	IC-RF CIRCUIT;ES6603S,LQFP,64P,10x10mm,P	
RL1	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
RL2	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
RN1	2011-000475	R-NET;33OHM,5%,1/16W,L,CHIP,8P,TP,32	
RN2	2011-000475	R-NET;33OHM,5%,1/16W,L,CHIP,8P,TP,32	
RN3	2011-000475	R-NET;33OHM,5%,1/16W,L,CHIP,8P,TP,32	
ROC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
ROR2	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR11	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR15	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
RR16	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608	
RR17	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR18	2007-000965	R-CHIP;5.1Kohm,5%,1/10W,TP,1608	
RR19	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR20	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR21	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR22	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR24	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR25	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR26	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR27	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR28	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR29	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR3	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
RR32	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR36	2007-001694	R-CHIP;12Kohm,0.5%,1/10W,TP,1608	
RR37	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR39	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RR4	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
RR44	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
RR5	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
RR50	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR51	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR6	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
RR7	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR8	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	
RR87	2007-000033	R-CHIP;0ohm,5%,1/4W,TP,3216	
RR9	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
SDC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC43	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC49	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SDC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
SJACK	3722-001375	JACK-DIN;4P,-,NI,BLK,-	
U1	1204-002224	IC-PAL/NTSC DECODER;ES6698FD,P	DIFFERENT from MODELS
	1204-002260	IC-PAL/NTSC DECODER;ES6629F	DIFFERENT from MODELS
VAR32	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16	CIS Only
VAR33	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16	CIS Only
VAR34	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16	CIS Only
VBD1	3301-001461	BEAD-SMD;300ohm,1.6x0.8x0.8mm,300mA,TP,	
VBD2	3301-001461	BEAD-SMD;300ohm,1.6x0.8x0.8mm,300mA,TP,	
VC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC14	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	Not used CIS
VC15	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	Not used CIS
VC16	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	Not used CIS
VC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC30	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
VC44	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608	
VC50	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
VE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
VE2	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
VE4	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
VE5	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
VE6	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
VE7	2401-001479	C-AL;470UF,20%,10V,GP,TP,6.3*11MM,-	
VIC1	1204-001978	IC-VIDEO PROCESS;LA73054,-,36P,-,SSOP,7V	
VL1	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL3	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL4	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL5	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL6	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
VR10	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR11	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR17	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP	CIS Only
VR18	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	Not used CIS
VR19	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
VR2	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR20	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR21	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR3	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR32	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
VR33	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR34	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	
VR4	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR5	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR6	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR7	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR8	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR9	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VRC17	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	Not used CIS
VRC18	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16	CIS Only
VRC31	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
VSC1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
VZ10	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
VZ20	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
VZ21	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
VZ22	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
VZ23	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	
VZ5	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
VZ6	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
VZ7	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
VZ8	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
VZ9	0403-001083	DIODE-ZENER;UDZ9.1B,8.85-9.23V,200MW,UMD	Not used CIS
ZC47	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
ZC49	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608	
ZR49	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
ZR50	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark